

Наконечники кольцевые не изолированные

поперечное сечение провода 0.5~1.5mm² I_{max}=19A




Тип	Резьба, (дюйм)	Резьба d2 (мм)	Размеры (мм)					Dφ
			B	L	F	E	Dφ	
RNB 1.25-3	#4	3.2	5.7	12.6	4.95	4.8	3.4	1.7
RNBS 1.25-3.5	#6	3.7	5.7	12.6	4.95			
RNBM 1.25-3.5	#6	3.7	6.6	14.4	6.3			
RNBL 1.25-3.5	#6	3.7	7.2	15.5	7.0			
RNBS 1.25-4	#8	4.3	6.6	14.4	6.3			
RNBL 1.25-4	#8	4.3	8.0	15.8	7.0			
RNBS 1.25-5	#10	5.3	8.0	15.8	7.0			
RNBL 1.25-5	#10	5.3	9.5	17.5	8.0			
RNBLL 1.25-5	#10	5.3	11.6	21.8	11.1			
RNB 1.25-6	1/4	6.5	11.6	21.8	11.1			
RNB 1.25-8	5/16	8.4	11.6	21.8	11.1			
RNB 1.25-10	3/18	10.5	13.6	25.5	13.9			
RNB 1.25-12	1/2	13.0	19.2	30.4	16.0			

поперечное сечение провода 1.5~2.5mm² I_{max}=27A

Тип	Резьба, (дюйм)	Резьба d2 (мм)	Размеры (мм)					Dφ
			B	L	F	E	Dφ	
RNB 2-3	#4	3.2	6.6	12.3	4.3	4.8	4.1	2.3
RNBS 2-3.5	#6	3.7	6.6	12.3	4.3			
RNBM 2-3.5	#6	3.7	6.6	16.0	7.0			
RNBL 2-3.5	#6	3.7	8.5	16.8	7.75			
RNBS 2-4	#8	4.3	6.6	16.0	7.0			
RNBL 2-4	#8	4.3	8.5	16.8	7.75			
RNBS 2-5	#10	5.3	8.5	16.8	7.75			
RNBL 2-5	#10	5.3	9.5	16.8	7.75			
RNB 2-6	1/4	6.5	12.0	21.8	11.0			
RNB 2-8	5/16	8.4	12.0	21.8	11.0			
RNB 2-10	3/18	10.5	13.6	25.5	13.9			
RNB 2-12	1/2	13.0	18.0	29.0	16.0			

поперечное сечение провода 2.5~4mm² I_{max}=37A

Тип	Резьба, (дюйм)	Резьба d2 (мм)	Размеры (мм)					Dφ
			B	L	F	E	Dφ	
RNB 3.5-4	#8	4.3	8.0	18.0	7.7	6.0	5.0	3.0
RNBS 3.5-5	#10	5.3	8.0	18.0	7.7			
RNBL 3.5-5	#10	5.3	12.0	21.4	7.7			
RNB 3.5-6	1/4	6.5	12.0	21.4	7.7			
RNB 3.5-8	5/16	8.4	15.0	27.0	13.5			
RNB 3.5-10	3/8	10.5	15.0	27.0	13.5			



поперечное сечение провода 4~6mm² I_{max}=48A

Тип	Резьба, (дюйм)	Резьба d2 (мм)	Размеры (мм)					dφ
			B	L	F	E	Dφ	
RNB 5.5-3.5	#6	3.7	7.2	15.7	5.9	6.8	5.6	3.4
RNBS 5.5-4	#8	4.3	7.2	15.7	5.9			
RNBL 5.5-4	#8	4.3	9.5	19.8	8.3			
RNB 5.5-5	#10	5.3	9.5	19.8	8.3			
RNB 5.5-6	1/4	6.5	12.0	25.8	13.0			
RNB 5.5-8	5/16	8.4	15.0	28.0	13.7			
RNB 5.5-10	3/8	10.5	15.0	28.0	13.7			
RNB 5.5-12	1/2	13.0	19.2	32.4	16.0			

поперечное сечение провода 6-10 мм² I_{max} = 62A

Тип	Резьба, (дюйм)	Резьба d2 (мм)	Размеры (мм)					
			B	L	F	E	Dφ	dφ
RNB 8-4	#8	4.3	8.8	23.8	9.3	8.5	7.2	4.5
RNBS 8-5	#10	5.3	8.8	23.8	11.1			
RNBM 8-5	#10	5.3	12.0	23.8	9.3			
RNBL 8-5	#10	5.3	15.0	29.8	13.8			
RNBS 8-6	1/4	6.5	12.0	23.8	9.3			
RNBL 8-6	1/4	6.5	15.0	29.8	13.8			
RNB 8-8	5/16	8.4	15.0	29.8	13.8			
RNB 8-10	3/8	10.5	15.0	29.8	13.8			
RNB 8-12	1/2	13.0	20.0	33.5	15.0			




поперечное сечение провода 10-16 мм² I_{max} = 88A

Тип	Резьба, (дюйм)	Резьба d2 (мм)	Размеры (мм)					
			B	L	F	E	Dφ	dφ
RNB 14-4	#8	4.3	12.0	29.8	13.3	10.5	9.0	5.8
RNB 14-5	#10	5.3	12.0	29.8	13.3			
RNBS 14-6	1/4	6.5	10.0	28.8	13.3			
RNBL 14-6	1/4	6.5	16.0	32.8	13.3			
RNB 14-8	5/16	8.4	16.0	32.8	14.5			
RNB 14-10	3/8	10.5	16.0	32.8	14.5			
RNB 14-12	1/2	13.0	22.0	41.0	19.5			

поперечное сечение провода 16-25 мм² I_{max} = 115A

Тип	Резьба, (дюйм)	Резьба d2 (мм)	Размеры (мм)					
			B	L	F	E	Dφ	dφ
RNBS 22-5	#10	5.3	12.2	33.2	14.5	12.0	11.5	7.7
RNBL 22-5	#10	5.3	16.5	33.7	13.5			
RNBS 22-6	1/4	6.5	12.2	33.2	14.5			
RNBL 22-6	1/4	6.5	16.5	33.7	13.5			
RNB 22-8	5/16	8.4	16.5	33.7	13.5			
RNB 22-10	3/8	10.5	16.5	33.7	13.5			
RNB 22-11	7/16	11.5	22.0	42.5	19.5			
RNB 22-12	1/2	13.0	22.0	42.5	19.5			



поперечное сечение провода 35-50 мм² I_{max} = 160A

Тип	Резьба, (дюйм)	Резьба d2 (мм)	Размеры (мм)					
			B	L	F	E	Dφ	dφ
RNB 38-5	#10	5.3	15.3	39.0	18.3	14.0	13.3	9.4
RNB 38-6	1/4	6.5	15.3	39.0	18.3			
RNBS 38-8	5/16	8.4	15.3	39.0	18.3			
RNBL 38-8	5/16	8.4	22.0	42.7	17.7			
RNBS 38-10	3/8	10.5	15.3	39.0	18.3			
RNBL 38-10	3/8	10.5	22.0	42.7	17.7			
RNB 38-11	7/16	11.5	22.0	42.7	17.7			
RNB 38-12	1/2	13.0	22.0	42.7	17.7			

поперечное сечение провода 50-70 мм² I_{max} = 215A

Тип	Резьба, (дюйм)	Резьба d2 (мм)	Размеры (мм)					
			B	L	F	E	Dφ	dφ
RNB 60-6	1/4	6.5	22.0	49.7	20.7	18.0	15.4	11.4
RNB 60-8	5/16	8.4						
RNB 60-10	3/8	10.5						
RNB 60-11	7/16	11.5						
RNB 60-12	1/2	13.0						
RNB 60-14	9/16	15.0	32.0	57.5	23.5	18.0	15.4	11.4
RNB 60-16	5/8	17.0						
RNB 60-18	11/16	19.0						
RNB 60-20	3/4	21.0						
RNB 60-22	7/8	23.0						



поперечное сечение провода 70-95 мм² I_{max} = 235A

Тип	Резьба, (дюйм)	Резьба d2 (мм)	Размеры (мм)					
			B	L	F	E	Dφ	dφ
RNB 70-6	1/4	6.5	24.0	50.0	20.0	19.0	17.5	13.0
RNB 70-8	5/16	8.4						
RNB 70-10	3/8	10.5						
RNB 70-11	7/16	11.5						
RNB 70-12	1/2	13.0						
RNB 70-14	9/16	15.0	32.0	61.0	26.0	19.0	17.5	13.0
RNB 70-16	5/8	17.0						
RNB 70-18	11/16	19.0						
RNB 70-20	3/4	21.0						
RNB 70-22	7/8	23.0						

поперечное сечение провода 95-120 мм² I_{max} = 255A

Тип	Резьба, (дюйм)	Резьба d2 (мм)	Размеры (мм)					
			B	L	F	E	Dφ	dφ
RNB 80-6	1/4	6.5	22.0	54.2	20.7	20.0	19.5	14.5
RNB 80-8	5/16	8.4						
RNB 80-10	3/8	10.5						
RNB 80-11	7/16	11.5						
RNB 80-12	1/2	13.0						
RNB 80-14	9/16	15.0	32.0	68.0	32.0	20.0	19.5	14.5
RNB 80-16	5/8	17.0						
RNB 80-18	11/16	19.0						
RNB 80-20	3/4	21.0						
RNB 80-22	7/8	23.0						

поперечное сечение провода 120-150 мм² I_{max} = 300A

Тип	Резьба, (дюйм)	Резьба d2 (мм)	Размеры (мм)					
			B	L	F	E	Dφ	dφ
RNB 100-6	1/4	6.5	28.5	55.6	20.4	21.0	22.1	16.4
RNB 100-8	5/16	8.4						
RNB 100-10	3/8	10.5						
RNB 100-11	7/16	11.5						
RNB 100-12	1/2	13.0						
RNB 100-14	9/16	15.0	32.0	69.0	32.0	21.0	22.1	16.4
RNB 100-16	5/8	17.0						
RNB 100-18	11/16	19.0						
RNB 100-20	3/4	21.0						
RNB 100-22	7/8	23.0						

