BAT54A DIODE

SCHOTTKY BARRIER (DUAL) DIODES


■ DESCRIPTION


Planar Schottky barrier diodes are encapsulated in the SOT-23 small plastic SMD package. Single diodes and dual diodes with different pin configuration are available.

■ FEATURES

- * Low forward voltage
- * Guard ring protected
- * Small plastic SMD package

■ SYMBOL






■ ORDERING INFORMATION

Ordering Number	Package	Pin Assignment			Dookina	
		1	2	3	Packing	
BAT54AG-AE3-R	SOT-23	K1	K2	A2A1	Tape Reel	

Note: Pin Assignment: A: Anode K: Cathode



MARKING



<u>www.unisonic.com.tw</u> 1 of 3

BAT54A DIODE

■ **ABSOLUTE MAXIMUM RATINGS** (T_A = 25°C, unless otherwise specified)

PARAMETER	SYMBOL	RATINGS	UNIT		
PER DIODE					
Continuous Reverse Voltage	V_R	30	V		
Continuous Forward Current	I _F	200	mA		
Repetitive Peak Forward Current (t _P <1s, δ≤0.5)	I _{FRM}	300	mA		
Non-repetitive Peak Forward Current (t _P <10ms)	I _{FSM}	600	mA		
Junction Temperature	T_J	+125	°C		
Storage Temperature	T _{STG}	-60 ~ + 150	°C		
PER DEVICE					
Power Dissipation (T _A ≤25°C)	P_D	230	mW		

Note: Absolute maximum ratings are those values beyond which the device could be permanently damaged. Absolute maximum ratings are stress ratings only and functional device operation is not implied.

■ THERMAL DATA

PARAMETER	SYMBOL	RATINGS	UNIT
Junction to Ambient	θ_{JA}	500	°C/W

■ **ELECTRICAL CHARACTERISTICS** (T_A = 25°C, unless otherwise specified)

PARAMETER	SYMBOL	TEST CONDITIONS	MIN	TYP	MAX	UNIT
Forward Voltage (See Fig.1)	V _F	$I_F = 0.1 \text{mA}$			240	mV
		$I_F = 1mA$			320	mV
		I _F = 10mA			400	mV
		$I_F = 30mA$			500	mV
		I _F = 100mA			800	mV
Reverse Current (See Fig.2)	I _R	V _R = 25V			2	μΑ
Reverse Recovery Time (see Fig.4)	t _{rr}	When switched from I _F =10mA				
		to $I_R = 10 \text{mA}$, $R_L = 100 \Omega$			5	ns
		measured at I _R = 1mA				
Diode Capacitance (see Fig.3)	C_D	$f = 1 MHz, V_R = 1V$			10	рF

BAT54A DIODE

■ TYPICAL CHARACTERISTICS




Fig.1 Forward current as a function of forward voltage; typical values.




Fig.2 Reverse current as a function of reverse voltage; typical values.




Fig.3 Diode capacitance as a function of reverse voltage; typical values.




Fig.4 Reverse recovery definitions

UTC assumes no responsibility for equipment failures that result from using products at values that exceed, even momentarily, rated values (such as maximum ratings, operating condition ranges, or other parameters) listed in products specifications of any and all UTC products described or contained herein. UTC products are not designed for use in life support appliances, devices or systems where malfunction of these products can be reasonably expected to result in personal injury. Reproduction in whole or in part is prohibited without the prior written consent of the copyright owner. The information presented in this document does not form part of any quotation or contract, is believed to be accurate and reliable and may be changed without notice.